

Self-Service Terminal

HIGH SERVICE AND EFFICIENCY

Modern shopping experiences

The ANKER Self-Service terminal offers customers a smooth, convenient shopping experience while easing the burden on cashiers. The additional checkout stations reduce queues and increase customer throughput. Cashiers at stationary checkouts can now operate on the sales floor to actively improve customer service there. The self-checkout is easy to operate and manage.

Advantages

- Flexibility through modular design
- Simple software integration due to standard peripherals
- Reliability due to high-quality brand components
- UX design for high customer acceptance
- Space-saving footprint and low installation depth
- LED status illumination
- Intuitive control panel
- Compatible with all common payment terminals
- Slim and frameless design
- Available as a stand-alone model (for column mounting, desktop table mounting or as a table solution) or for wall mounting

Payment options

- Depending on the used payment terminal*
- Depending on the installed software
- Optional connection to cash management systems

Field of application

- Food retail, DIY, drugstore, retail, gastronomy etc.

Configuration

1 23,8" touchscreen	4 Barcode scanner
2 Receipt printer	5 Changeable design covers
3 Device-specific holder for a payment terminal*	

Change without notice

*Payment terminal not included in the scope of delivery

Kiosk in RAL9016 deep white



Kiosk in RAL9005 deep black



ANKER Self-Service Terminal

Technical data at a glance. Your guide to the right product.

<u>Model</u>	S238-II
<u>Width x height x depth in mm</u>	335 x 910 x 168
<u>Touchscreen</u>	23,8" 1920 x 1080 px display brightness with 450 cd/m ²
<u>Barcode scanner</u>	Honeywell CM2D
<u>Receipt printer</u>	EPSON Printer TM-m30II black EU LAN PS EPSON Printer TM-T88VI USB/LAN/SERIELL/NFC
<u>Illumination</u>	Integrated status LED
<u>Other features</u>	Changeable design cover
<u>Operating system and technical equipment</u>	<u>Windows</u> Chipset: ASROCK, Board IMB-1222-WV Q470 mITX comet lake Processor: Intel I3-10100TE CPU 2,3GHz Memory: DDR4 8GB Hard Drive: ATP AF128GSTIC SSD M.2 128 GB SATA 6Gb/s TLC Preinstalled OS: Windows 10 IoT LTSC 2021
	<u>Android</u> Chipset: Cortex-A73x4+Cortex-A53x2 Processor: Amlogic A311D 6-core ARM Memory: 4GB DDR3 Hard Drive: 16GB eMMC Flash; Graphic GPU: Mali G52 MP4 Preinstalled OS: Standard: Android 9.0 (Linux 4.9)
<u>Data connection</u>	LAN/WLAN/Bluetooth

Subject to change without notice


Accessories




Stand
item no.:
58500.001-0070



**Kiosk surface and ACR
mount** item no.:
13300.285-00x1



Kiosk wall mounting
item no.:
13300.294-00x0



**Adapter for combining ACR
with kiosk for wall mounting**
item no.: 13300.296-00x1

For the combination of kiosk on the ACR, please order art. no. 13300.285-00x1.
Art. nos. 13300.294-00x0 and 13300.296-00x1 are required for a combination of kiosk and ACR as wall mounting.

